

⚠ WARNINGS AND CAUTIONS

- Make sure **POWER** is **COMPLETELY OFF** at the fuse box
- Have your fixture installed by a qualified licensed electrician
- Prepare everything in a clear area
- Wear gloves at all times during this installation
- Read instructions carefully before you start assembly
- Keep this installation sheet for future reference

Please Note:

- This Alora LED fixture comes with pre-wired LED module(s)
- Unless instructed, Do Not touch any part of the LED module(s) as any unnecessary contact with the module could cause permanent damage
- For dimming, an ELV (Electronic Low Voltage) or TRIAC type of dimmer is required
- 120-277V input

NOTICE

- The important safeguards and instructions outlined in this sheet cannot cover all possible conditions and situations that may occur. It must be understood that caution and certain care factors must be followed. These instructions are provided for your safety and we highly recommend that a licensed, trained electrician install this unit.
- This fixture is designed to be mounted on a correctly installed standard round or octagon box OR through a wiring box with a plaster frame. The box must be securely mounted to the structure of the building. The crossbar and hardware supplied should be used, directly mounting the fixture to the outlet box may make it impossible to correctly align the fixture.

ASSEMBLY INSTRUCTIONS

Step 1

Remove the mounting plate (1d) from within the canopy (2d) by loosening the four mounting screws provided (2c). Attach the mounting plate (1d) to the junction box (1a) using two junction box screws (not provided) (1e). *For additional support install four anchor screws (1h) and anchors (1g) through mounting plate into ceiling*.

Step 2

Select the desired length you wish the pendant (3a) to hang by pushing/pulling the cord through the cord adjuster mechanism and secure the wire using the allen key provided (2a). Attach safety cables (2b) to the safety mounting loops (1f) to ensure fixture is secure. Connect fixture wires to junction box wires using the marrettes provided (1b). (white to white "N", black to black "L", green to green "G"). Now connect the canopy (2d) to the mounting plate (1d) using the four mounting screws provided (2c).

Step 3

Install recommended lamps (not provided) (referred on the socket label for maximum wattage and type) to fixture and restore power. * If fixture has integrated LED (Light Emitting Diodes) lamp installation is not required.

You are now ready to enjoy your fixture.

